006280"6ES7S960



Fig. 1

Local Memory Data Descriptors



237

Channel Control byte (CCNTRL)

7	6	5	4	3	2	1	0
Reserved		Soft Flag1	Soft Flag0	Command Completion Status			

Command Completion Status

0	*Reserved / Unused Channel*
1	Completed with No Errors
2	Zero bytes in "Transfer size" field in CCD (LM only)
3	Zero bytes in "Segment size" field in FD
4	PCI Frame Overrun
5	LM Frame Overrun
6	*Reserved*
7	PCI Abort Error during transfer
8	PCI Parity Error during transfer (PCI Read Only)
9-F	*Reserved*

Fig. 2

PTI Data Descriptors



PTI Chanel Control byte (PTI CCNTRL)

IRQ per Seg	Dump Data	Soft Flag1	Soft Flag0	Command Completion Status			
7	6	5	4	3	2	1	0

Command Completion Status

0	*Reserved / Unused Channel*
1	Completed with No Errors
2	Zero bytes in "Transfer size" field in CCD (LM only)
3	Zero bytes in "Segment size" field in FD
4	PCI Frame Overrun
5	LM Frame Overrun
6	Unit Start Indicator detected
7	PCI Abort Error during transfer
8	PCI Parity Error during transfer (PCI Read Only)
9-F	*Reserved*

Fig. 3

0605150-0800